

POWERED ZONE CONTROLLER



## OVERVIEW

Designed for in-room and in-rack systems, the 251 Powered Zone Controller contains all the functionality needed to create a great sounding and flexible Hi-Res Audio zone.

With two powerful, cool-running channels of on-board amplification, the Meridian 251 can comfortably drive a pair of loudspeakers or a sound bar with our trade mark fidelity and high resolution performance. With a pair of analogue outputs, you can also run a 2.1 system with a separate subwoofer.

With both digital and analogue inputs, the MQA-enabled Meridian 251 is a hub for distributed audio applications from simple single zone to whole-house distribution. Featuring IP and IR control, this versatile 1U, half-width unit can be easily installed behind a TV or in a rack.

Simple web-based setup page makes for easy, repeatable and quick configuration. Our 251 is also an endpoint for our award-winning Sooloos music management platform as well as offering support for Roon.

## PRODUCT HIGHLIGHTS

- 2 x 100W per channel into 4 Ohms (2 x 65W per channel into 8 Ohms), cool-running amplifiers with a high peak output current capability to drive difficult loads and 40kHz true Hi-Res bandwidth.
- Housed in a half-width, 1U tall Aluminium enclosure and available with an optional rack-mount kit or VESA

mount bracket, the 251 has multiple installation applications.

 Endpoint for our award-winning Sooloos music management platform, along with Roon support, for a user-friendly Hi-Res Audio experience.

- Built-in MQA decoder, the Meridian 251 fully supports Master Quality Authenticated encoded music playback, guaranteeing a studio master quality experience.
- $\cdot$   $\,$  IP Control allows for seamless integration and

## USER FEATURES

- A significant number of control options are provided on the Meridian 251 Powered Zone Controller, including IP control, native iPad network control app, Meridian Sooloos Control, IR and third party control.
- In addition, the unit's front panel features multiple LEDs to indicate source selection, including one that signals MQA playback
- · Configuration via in-built webpage to select all installation options.

## TECHNOLOGIES

### LIP SYNC

Video processing typically delays the picture. For installations where the audio and video are separated before video processing, the Meridian 251 has adjustable 80ms audio delay to realign the audio with the video.

### FIFO RECLOCKING

Clock variations, known as jitter, are one the main causes of unpleasant "glare" in digital audio systems. The Meridian 251 solves this problem with our proprietary jitter reduction technique using a FIFO (first-in firstout) buffer that allows an independent output clock to deliver clock performance that does not rely upon on the incoming signal quality.

### DSP UPSAMPLING AND APODISING FILTERS

flexibility within the home.

level analogue outputs.

Also includes digital and analogue inputs and line-

Made in Britain and backed by our 5 year warranty.

Almost all audio has been digitally processed, even if it arrives at the Meridian 251 in analogue form. Upsampling allows the Meridian 251's DACs to run at a higher sample rate and achieve their full potential. Upsampling also provides the opportunity to apply apodising correction to ameliorate time-domain errors that have been introduced to the signal by the ADCs or other upstream processing.

### MQA

Master Quality Authenticated (MQA) is a revolutionary end-to-end technology that delivers master quality audio in a file that's small enough to stream or download.



## SPECIFICATION

AUDIO OUTPUTS	Speaker outputs on Phoenix connectors 24-12 AWG Compatible					
	+ 2 x 100w into 4 $\Omega$ nominal load (2 x 65w into 8 $\Omega)$ + 40kHz Bandwidth					
	2-channel line-level analogue output on RCA phono connectors					
	• Twin 192kHz 24-bit DACs					
AUDIO INPUTS	• One 2-channel digital coaxial S/PDIF input. 44.1kHz to 192kHz sampling and up to 24-bit					
	• One 2-channel Meridian SpeakerLink input. 44.1kHz to 192kHz sampling and up to 24-bit					
	One 2-channel digital optical TOSLINK input. 44.1kHz to 96kHz sampling and up to 24-bit					
	One 2-channel analogue input on RCA phono connectors					
	• One network input (Ethernet) for connection to Meridian Sooloos or third party control interface					
CONTROL SIGNALS	IP Control					
	• IR on 3.5mm jack					
	Meridian Comms					
DISPLAY	LEDs to indicate source selection and MQA status					
POWER	• Advanced linear power supply: 110–120V ac 50–60Hz   220-240V ac 50-60Hz					
DIMENSIONS	HEIGHT: 42mm (without feet) WIDTH: 203mm					
	DEPTH: 221mm (226mm inc. connectors) WEIGHT: 2.5kg					
RACK-MOUNTING	• 1U tall rack kit available with space for two units					
	Optional VESA mount brackets					

# 251 POWERED ZONE CONTROLLER POWERFUL CONTROL

Designed for use in-room or in-rack, the 251 Powered Zone Controller contains the functionality needed to create a powered Hi-Res audio zone. The Meridian 251 features two powerful, high performance, cool-running 100W Class D Amplifiers that allow this versatile 1U tall product to be easily partnered with any passive loudspeaker. Accommodating both local and distributed audio, whether analogue or digital, the MQA-enabled Meridian 251 is also an endpoint for our award-winning Sooloos music management platform, along with Roon support.

Control features including IP and IR allow this versatile solution to be seamlessly integrated into the home.

MERIDIAN	251 Powered Zone Controller							
	Aı			Oı	Net			
	۲	•	•					





# THE 251 AT A GLANCE



Speaker-level outputs enable the 251 to work with any passive loudspeaker. Additional line-level outputs provide further flexibility and simple subwoofer integration.



Compact and easy to install - 1U form factor with optional rack kit.



Lip Sync to realign audio and video following separation.



IP, IR, Trigger and Third Party control options enable seamless integration and flexibility within the home.



meridian-audio.com



Multiple input options, including optical and coax digital and analogue.



MHR – Unique Meridian High Resolution MHR up-sampling to offer the best possible performance and lossless audio performance from all of your sources.



MQA delivers master quality audio in a file that's small enough to stream or download.



Cost effective solution in multiple installation applications, enabled by Meridian's complimentary Design and Specification Service.

For full details, contact: design@meridian.co.uk +44 (0)1480 445678



# SOOLOOS: ALL MUSIC. ALL THE TIME.

Meridian's award-winning Sooloos delivers pristine lossless audio quality with an extremely intuitive user interface.

It automatically discovers and integrates with your client's network for instant installation. Sooloos is a modular, expandable system designed to suit your needs.



## $\blacktriangleright$

STREAMING TIDAL, Napster & Rhapsody



Easy to input & catalogue over 30,000 CDs DOWNLOAD LIBRARY MP3, Flac & Wav



INTERNET RADIO TuneIn Radio

# MERIDIAN SOOLOOS AT A GLANCE

### 

Allows you to move away from text based searching forever. Choose from genres, moods, decades, resolution quality and more to find exactly what you want to listen to.



## SWIM

When your queued music comes to an end, Swim will keep the party going. Unique to Sooloos, this is the most sophisticated way to randomise your favourite music.



## BROWSE

Effortlessly browse by artist, release date, TuneIn Radio stations or import date using the stunning free iPad or Touch PC interfaces.



### EXPLORE

Sooloos offers myriad ways to navigate 30,000 album capacity. Browse by genre, tags, decade, mood, words or ideas. Explore makes it simple to find what you want to hear.



## STREAM

Add millions of songs to your collection with major music subscription services, like Tidal, and simply add any music you like to your collection to listen to them time and time again.

## ((1)) TUNE IN

Internet Radio offers a vast catalogue of music, entertainment and information from around the world. Find stations and listen easily and reliably thanks to the integrated TuneIn<sup>TM</sup> directory.